



## DMX CHART – LUXIBEL B PAR360Z

### 5-Channel Mode

| Channel | Value | Function |
|---------|-------|----------|
| CH 1    | 0-255 | Red      |
| CH 2    | 0-255 | Green    |
| CH 3    | 0-255 | Blue     |
| CH 4    | 0-255 | White    |
| CH 5    | 0-255 | Zoom     |

### 8-Channel Mode

| Channel | Value | Function      |
|---------|-------|---------------|
| CH 1    | 0-255 | Coarse dimmer |
| CH 2    | 0-255 | Red           |
| CH 3    | 0-255 | Green         |
| CH 4    | 0-255 | Blue          |
| CH 5    | 0-255 | White         |
| CH 6    | 0-255 | CCT           |
| CH 7    | 0-255 | Strobe        |
| CH 8    | 0-255 | Zoom          |

### 12-Channel Mode

| Channel | Value | Function      |
|---------|-------|---------------|
| CH 1    | 0-255 | Coarse dimmer |
| CH 2    | 0-255 | Red           |
| CH 3    | 0-255 | Green         |
| CH 4    | 0-255 | Blue          |
| CH 5    | 0-255 | White         |
| CH 6    | 0-255 | CCT           |
| CH 7    | 0-255 | Master Color  |
| CH 8    | 0-255 | Strobe        |
| CH 9    | 0-255 | Zoom          |
| CH 10   | 0-255 | Dimmer Curve  |
| CH 11   | 0-255 | Frequency     |
| CH 12   | 0-255 | Fan Speed     |

## 17-Channel Mode

| <b>Channel</b> | <b>Value</b> | <b>Function</b> |
|----------------|--------------|-----------------|
| CH 1           | 0-255        | Coarse Dimmer   |
| CH 2           | 0-255        | Fine Dimmer     |
| CH 3           | 0-255        | Red             |
| CH 4           | 0-255        | Fine Red        |
| CH 5           | 0-255        | Green           |
| CH 6           | 0-255        | Fine Green      |
| CH 7           | 0-255        | Blue            |
| CH 8           | 0-255        | Fine Blue       |
| CH 9           | 0-255        | White           |
| CH 10          | 0-255        | Fine White      |
| CH 11          | 0-255        | CCT             |
| CH 12          | 0-255        | Master Color    |
| CH 13          | 0-255        | Strobe          |
| CH 14          | 0-255        | Zoom            |
| CH 15          | 0-255        | Dimmer Curve    |
| CH 16          | 0-255        | Frequency       |
| CH 17          | 0-255        | Fan Speed       |