

# Master Light (3.2)

Master Layer Light 3.2				13 channels	
Function	DMX	DMX (16bit)	Default	Range	Notes
Level	1		255	0-255	
Brightness	2		128	0-255	
Contrast	3		128	0-255	
Live Mask	4		0	0-255	
Video Map Enable	5		0	0-127	Disabled
				128-255	Enabled
Video Map Mixmode	6		0	0-255	
Mix Morph	7		0	0-127	Mix
				128-255	Morph
Map select A	8		0	0-255	
Map Select B	9		0	0-255	
Audio Volume	10		255	0-255	
Region Mapper	11		0	0-127	Enable
				128-255	Disable
Shift	12		128	0-255	
Sat	13		128	0-255	